

Wound Beads (2961666681)



Part Number: 2961666681

61 WOUND BEAD

Explanation of Part Numbers:

- Digits 1 & 2 = Product Class
- Digits 3 & 4 = Material Grade
- Last digit 1 = Bulk Packed 4 = Taped and Reeled

Six and eleven hole beads, in two NiZn materials, are available both as beads (product class 26) and wound with tinned copper wire in several winding configurations (product class 29).

- Wire used for winding is oxygen free high conductivity copper with 100% matte tin plating over a nickel undercoating.
- Recommended storage temperature and operating temperature is -55 °C to 125 °C

Packaging Options:

- Parts with a 1 as the last digit of the part number are supplied bulk packed. Wound beads with part numbers 29- 666631 and 29- 666651 can be supplied radially taped and reeled per IEC 60286-1 and EIA 468- B standards. For these taped and reeled wound beads the last digit of the part number is a 4. Taped and reeled wound beads are supplied 500 pieces on a 13 reel.

For any wound bead requirement not listed in here, please contact our customer service group for availability and pricing.

Weight: 1.4 (g)

Dim	mm	mm tol	nominal inch	inch misc.	Winding Information			
A	6	±0.25	0.236	-	Turns Tests	Wire Size	1st Wire Length	2nd Wire Length
B	0.75	+0.15	0.032	-	2 x 1½	0.53	38.0 ±3.0	28.0 ±3.0
C	10	±0.25	0.394	-		24 AWG	(1.500")	(1.102")
D	3.5	Ref	0.138	Ref				

Chart Legend

- + Test frequency
- A ½ turn is defined as a single pass through a hole.

Typical Impedance (Ω)	
10 MHz	75
50 MHz ⁺	280
100 MHz ⁺	380
200 MHz ⁺	510
400 MHz	600

- Beads are controlled for impedance limits only. Minimum impedance values are specified for the + marked frequencies. The minimum impedance is typically the listed impedance less 20%.

The 44 material beads and wound beads are tested on the 4193A Vector Impedance Meter. The 61 material parts on the 4291A RF Impedance Analyzer.

